

Auditorium Normal Circuit Lighting Schedule

Circuit / Zone	Location	Elect Dwg.	Dimmer Panel	Dimmer Circuit #	Fixture Type	Quantity	Watts each	Raceway to wireway
AL-1	Entry level side aisles	E101	DR4	328	A2	2	150	HOME
	Entry level side aisles	E101	DR4	328	A14	6	75	HOME
	Entry level box seats	E101	DR4	328	A8B	6	150	HOME
AL-2	Auditorium Exit signs	E101, 102	DR4	329	X4	8	40	HOME
AL-3	Entry level	E101	DR4	330	A8A	12	150	HOME
AL-4	Entry & Bal level steplights	E101, 102	DR4	331	A2	16	50	HOME
AL-5	Balcony Level	E102	DR4	332	A9	8	50	HL-1 & HR-1
AL-6	Soundlocks	E101, 102	DR4	333	A3	4	150	HOME
AL-7a	House liner wallwashers	E103	DR4	334	A7	4	375	HL-1
AL-7b	House liner wallwashers	E103	DR4	335	A7	4	375	HL-1
AL-7c	Balcony wood wall	E104	DR4	336	A16	8	100	HL-1
AL-8a	W horizontal house LTG pipe	E103	DR4	337	A6	5	375	HL-1
AL-8b	E horizontal house LTG pipe	E103	DR4	338	A6	5	375	HR-1
AL-9	Catwalk # 1	E104	DR4	339	A5	6	375	HR-1
AL-10a	Catwalk # 2	E104	DR4	340	A5	6	375	HR-1
AL-10b	Catwalk # 2	E104	DR4	341	A5	6	375	HR-1
AL-11	House lighting pipe	E104	DR4	342	A5B	6	375	HR-1
AL-12	Catwalk	E104	DR4	343	A5C	6	375	HR-1
AL-13	Seat lighting	E201,203	DR4	344	Seat LTG	44	4	HOME

Auditorium Emergency Circuit Lighting Schedule

Emer Circuit	Normal Dim at same light	Location	Elect. Dwg	Fixture Type	Quantity	Watts each
ED1-1 / CB-1	AL-2 (#329)	Auditorium Exit signs	E101,E102	X6	8	40
ED1-2 / CB-2	AL-3 (#330)	Entry level seating	E101	A8A	3	150
ED1-3 / CB-3	AL-6 (#333)	Soundlocks	E101,E102	A3	4	150
ED1-4 / CB-4	AL-4 (#331)	Step Lights	E101,E102	A2	16	50
ED1-5 / CB-5	AL-12 (#343)	Balcony seating	E104	A5C	2	375
ED1-6 / CB-6	AL-13 (#344)	Seat lighting	E104	Seat LTG	44	4
ED1-7 / CB-7	AL-9 (#339)	Catwalk	E104	A5	2	375
ED1-8 / CB-8	AL-10b (#341)	Catwalk # 2	E104	A5/A5B	4	375